

INSTRUCTION DATA

PRODUCT: **ENFORCER**

VER: **2.1**

DATE: **MARCH 2001**



ENFORCER INSTRUCTIONS

Congratulations! Housed within this pack is one of the most versatile portable lighting systems available today.

Your Enforcer handheld light has several features that make it unique such as: Two lighting modes, a high output 30W Xenophot™ bulb for the ultimate in a long range beam and for long battery life, three LED lights give you a soft, long lasting general use light source.

Each Enforcer Pack allows the user to convert between a rechargeable, cordless 12 volt Nickel Metal Hydride (Ni-MH) battery and a 12 volt coil cord which allows your Enforcer to be powered from a vehicle or alternative 12 volt source such as one of our portable power packs.

Your Enforcer battery can be charged from 12-24 volts DC via the supplied cig plug adaptor or 100-240volts AC, and comes standard with wall plug adaptors for use overseas as well as at home!

FEATURES

- 3.5 amp rechargeable Ni-MH battery
- Battery pack snaps on and off easily
- Coil cord with cigarette lighter plug for alternative 12 volt use
- Compact but powerful 170mm reflector diameter
- Press button on-off switches
- Fast focusing beam - a LIGHTFORCE innovation
- Parabolic reflector with mirror finish for maximum lighting efficiency
- 30W Xenophot™ Xenon/Halogen bulb for high output
- Three LED lamps for long battery life
- Approximately 70 minutes of continuous use with fully charged battery.
- Approximately 18 hours in LED mode
- Multi voltage (12 - 24VDC and 100-240VAC) charging system.
- Interchangeable wall plugs on charger mains plug for simple international use.

RECOMMENDATIONS

- DO NOT clean your light with solvents. Use warm water and a soft cloth.
- DO NOT use greater than 35W bulb, the excess heat WILL damage your battery and LED lamps, this is not covered by warranty.
- We recommend you do not store your Enforcer with the battery pack attached as if it is accidentally switched on it may overdischarge the battery.
- Over discharge of your battery is harmful and should be avoided as it will damage your battery, we recommend recharging once your light beam is noticeably yellow.
- Store your Enforcer in a dry place.
- Do not immerse in water, Enforcers can be used in most weather, they are NOT WATERPROOF.
- Never leave your light face down, if accidentally switched on it can cause damage to the light and potentially ignite the surface
- Only use the battery charger that is supplied and recommended by Lightforce for charging your Enforcer battery pack, use of alternative charger may damage your battery and void warranty.

OPTIONS

- Additional 3.5Ah Ni-MH battery (#ENFBATNMH)
- 35 watt Longlife IRC bulb (#GL10)
- Clip-on filters - different patterns and colours available.

CHARGING INFORMATION

- The Ni-MH battery can be recharged at any level, it does not have to be discharged prior to charging.
- We recommend you remove the battery pack from your Enforcer prior to charging.
- Connecting your battery to charger:
 - a. Connect the output lead of the charger into the battery pack
 - b. Plug the output plug of your cig or wall mounted power supply into the socket on your battery charger.
 - c. Using either your cig plug for 12-24VDC connection or mains plug (with appropriate wall input plug) for 100-240VAC, power up your charger unit.
- The red CHARGING indicator light will illuminate when the battery is on charge
- The green READY indicator light will flash when your battery is fully charged
Leaving your charger on for extended periods of time can cause damage and void warranty.
Approximate charging time for a flat battery is 10hrs.
- After disconnecting your Enforcer battery from your charger, let it sit for approx 5 minutes or run the LED's for a minute or so before using the main bulb. (A fully charged battery straight from the charger can supply more voltage than the bulb can handle).

COMPONENT BREAKDOWN

